


CATALOG NUMBER	TYPE
CMAGU2RBRC - Black case Red LED	
CMAGU2RWRC - White case Red LED	



**Universal snap in canopy/junction box cover makes installation simple, secure and fast!**

#### FEATURES AND BENEFITS

Easy connect back plate or universal canopy	➤ Simple installation with hands free wiring
Light heads swivel 360°	➤ Maximum illumination where you need it
ETL Damp location listed	➤ Durable and long lasting performance
LED	➤ Dependable 25 year low-cost operation
Snap fit directional arrows	➤ Allows for placement in all applications
6V Battery	➤ Maintenance-free, rechargeable, heavy duty
Push to test switch	➤ Complies with fire codes
Dual voltage 120/277V	➤ No mixups and less inventory to carry

## RT Lighting, Magnatron

### Combination Emergency Exit Light

**Housing:** Injection-molded, V-O flame retardant, high-impact, thermoplastic housing. Compact, low profile design in a white or black finish.

**Illumination:** Energy efficient red or green LED. LED lamp life of 25 years plus. Energy consumption of less than 3 watts for red letters and less than 3 watts for green letters. Two fully adjustable 5.4 watt, glare-free lighting heads. High performance smooth thermoplastic reflector and polycarbonate lens for optimal light distribution and resistance to discoloration from natural or artificial light sources. Snap-in directional indicators. Exit letters are 6" high with a 3/4" stroke. Salida letters are 6" high with a 1/2" stroke.

**Option:** Remote capable unit available (option REM). REM option allows for operation of up to two additional 5.4 watt lighting heads. Consult factory for availability of remote heads.

**Battery:** 6V, sealed lead acid, maintenance-free, rechargeable.

**Charging Circuitry:** Internal solid-state transfer switch automatically connects the internal battery to the two lamp heads, illuminating them for a minimum of 90-minute emergency operation. Recharging the battery is initiated by a fully automatic solid-state, two-rate charger, which includes current limiting and temperature compensation to assure that optimum recharging rate, for even a fully discharged battery, will be accomplished in 12 hours.

**Electrical:** Universal transformer for 120 or 277V AC operation. Charge rate/power on LED indicator light. Periodic testing for three minutes, every thirty days is recommended to comply with local fire codes. LVD (low voltage discharge) feature activates to prevent battery from deep discharge, but not before the minimum 90-minute emergency operation. ETL Damp location listed. Red LED unit is C-UL (tested to C860) listed. Meets UL924, NFPA 101 Life Safety Code, and NEC requirements.

**Mounting:** Universal mounting canopy for side or top installation. Easy connect back plate snaps into place. Back plate and mounting canopy fit most standard junction boxes. Hardware included.